

FMJ PI MONOBLOC POWER AMPLIFIER

'Truly one of the finest power amplifiers on the market.'

CONTINUOUS POWER OUTPUT (20HZ-20KHZ AT 0.5% THD), PER CHANNEL

SINGLE CHANNEL, 8Ω, 20HZ-20KHZ 175W

SINGLE CHANNEL, 4Ω, AT 1KHZ 250W

HARMONIC DISTORTION, 80% POWER, 8Ω AT 1KHZ 0.003%

FREQUENCY RESPONSE +/- 0.2DB 20HZ - 20KHZ - 1DB AT 1HZ AND 100KHZ

RESIDUAL HUM AND NOISE TYPICALLY -112DB REF FULL POWER

VOLTAGE GAIN X28.3 (1 VOLT INPUT GIVES 100W/8Ω OUTPUT)

INPUT IMPEDANCE 22KOHMS IN PARALLEL WITH 470PF

GENERAL

POWER CONSUMPTION (MAXIMUM) 800VA

SIZE W/D/H MM. INC. FEET. 430 X 350 X 110

WEIGHT (NET) 12.5KG