

DV4001

Progressive Scan DVD Player



The DV4001 is more than just a DVD player: It handles movie DVDs, CDs (and their -R and -RW cousins), VCDs, MP-3 and WMA music discs, and JPEG-format photo discs, too! It delivers high image quality thanks to true progressive scan, an all-digital HDMI output, and internal scaling so you can really see the difference with whatever monitor you're using. You'll also appreciate the flutter-free movie reproduction provided by the 3:2 pulldown circuitry. There's also PAL <-> SECAM conversion for true world-wide compatibility. Sound quality is Marantz-standard, whether you choose stereo or multi-channel analog or coaxial or optical digital outputs. Conveniences range from on-screen display through parental control to front-panel menu operation. The remote controller fits your hand perfectly. Our three-year warranty provides peace of mind. And you've chosen a Marantz. You can't get better than that.

- Plays DVD-Video, DVD-R/RW, CD, CD-R/CD-RW, VCD 2.0, MP-3, WMA, DivX ULTRA and JPEG HD discs
- HDMI Output with scaling (1080i, 720p and 480p)
- Progressive scan with 3:2 pull-down film detection
- 192 kHz/24-bit audio D/A converters
- 108 MHz/12-bit video D/A converter
- PAL <- to -> NTSC Converter
- RS232C terminal for system control
- Low Profile Aluminum Front Panel

marantz[®]
LIFE AMPLIFIED[™]



| FEATURES | |
|---------------------------------|--|
| Separate Power Supply for Audio | - |
| DTS™ Decoder | - |
| Dolby Digital™ Decoder | ¥ |
| Disc Capacity | 1 |
| Progressive Scan | ¥ |
| 3:2 Pulldown | ¥ |
| Playback Formats | DVD-V, DVD-R/RW, DVD+R/RW, SVCD, VCD, CD, CD-R/RW, MP3, WMA, HD-JPEG, DivX Ultra |
| Video DAC | 108MHz/12-Bit |
| Audio DAC | 192kHz/24-Bit |
| HDAM | - |
| Video Circuit Off | ¥ |
| Display On/Off | ¥ |
| Zero-Impedance Plate | ¥ |
| Double Layerd Bottom Plates | - |
| Headphone | ¥ |
| Video Scaler | ¥ |
| Bass Management | - |
| Gold Plated Terminals | - |
| SOUND ENHANCEMENT | |
| Power Transformer | EI |
| Chassis | Metal |
| Lip-sync (digital audio delay) | - |
| IN/OUTPUTS | |
| VIDEO | |
| HDMI Out | 1 |
| Component Out | 1 |
| S-Video Out | 1 |
| Composite Out | 1 |
| AUDIO | |
| Analog Out (RCA) | 1 |
| 5.1ch Analog Out | - |
| Digital Optical Out | - |
| Digital Coaxial Out | 1 |
| i.Link (IEEE1394) | - |
| OTHER | |
| External control (RS232C) | ¥ |
| D-Bus Remote (RC-5) In/Out | 1/1 |
| Direct IR input | ¥ |

| SPECIFICATIONS | |
|--------------------------------|------------------------------|
| Freq. Response (Digital Audio) | 4Hz - 44kHz (DVD fs: 96kHz) |
| S/N Ratio | 110 dB |
| Dynamic Range | 100 dB |
| THD (1 kHz) | 0.0030% |
| GENERAL | |
| Color | Black |
| Front Panel | Aluminum |
| Remote Control | Device Remote RC001DV |
| Power Requirement | AC120-230V 50/60Hz |
| Power Consumption | 10W |
| Dimensions W x H x D (Inches) | 17 5/16" x 2 3/8" x 12 9/16" |
| Weight (lbs) | 8.8 |

marantz®
Life Amplified™

*All specifications, dimensions and weights are subject to change without notice.

D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

©2007 Marantz America, Inc. ¥ www.marantz.com